

MP-BC2

Multi-function Two in One Wifi Doorbell Camera



- 1/3 HD photosensitive chip Resolution: 1080P, 2MP
- One-click wake-up
- Real-time connection
- Real time two-way audio
- PIR detection, and alarm message Push
- Alarm Video playback
- More stable WIFI connection
- Built-in low power infrared lamp
- Max 32GB SD card for video recording
- PIR Function, Germany import PIR induction alarm, real time report
- ICR double filter, built-in low power infrared lamp
- Professional and customized WiFi antenna
- Ultra-low power consumption, standby time more than 180 days
- IP66 Waterproof
- Powered by a 7650mA polymer lithium battery



Model NO	MP-BC2
Operating system	Linux
Image sensor	1/3 million pixel CMOS
Minimum illumination	Color 0.6 lux@f1.2, black and white 0.08 lux@f1.2, 0 Lux ir Open
Day and night mode	Ir-cut Double Filter Automatic switching
Lens	2.8MM Million HD Lens
Video compression	H. 264, support for dual-code flow
Video mode	HD/SD
Maximum image size	Main stream 1920x1080; sub-code stream: 640x480;
Resolution	1080P: 2MP
Frame rate	25 Frames
Audio coding	G726, G711, AAC, MP3 format, 8K sampling rate, support echo cancellation function
Audio input	Built-in mic

Audio output	Internal speaker
Real Standby	Built-in MCU, support true standby function, support infrared, key, Gpio alarm
Wireless network	2.4GHz IEEE 802.11b/g/n
Storage Features	Support Micro SD card storage, Max 32G
Intelligent Alarm	PIR Human Temperature Detection
Infrared lamp	4 infrared light, 850nm, effective distance of 10 meters
Battery	7650 Ma polymer lithium battery, charge voltage: 5v2a
Standby time	180 days
Power	0.75W (work) 0.0025W (standby)
Working environment	-10°C~60°C/20%~85% (non condensation)